

## Transmission Media

- Transmission medium
  - Physical path between transmitter and receiver
  - May be guided (wired) or unguided (wireless)
  - Communication achieved by using EM waves
- Characteristics and quality of data transmission
  - Dependent on characteristics of medium and signal
  - Guided medium
    - \* Medium is more important in setting transmission parameters
  - Unguided medium
    - \* Bandwidth of the signal produced by transmitting antenna is important in setting transmission parameters
    - \* Signal directionality
      - Lower frequency signals are omnidirectional
      - Higher frequency signals can be focused in a directional beam
- Design of data transmission system
  - Concerned with data rate and distance
  - Bandwidth
    - \* Higher bandwidth implies higher data rate
  - Transmission impairments
    - \* Attenuation
    - \* Twisted pair has more attenuation than coaxial cable which in turn is not as good as optical fiber
  - Interference
    - \* Can be minimized by proper shielding in guided media
  - Number of receivers
    - \* In a shared link, each attachment introduces attenuation and distortion on the line

## **Guided transmission media**

- Transmission capacity (bandwidth and data rate) depends on distance and type of network (point-to-point or multipoint)
- Twisted pair
  - Least expensive and most widely used
  - Physical description
    - \* Two insulated copper wires arranged in regular spiral pattern
    - \* Number of pairs are bundled together in a cable
    - \* Twisting decreases the crosstalk interference between adjacent pairs in the cable, by using different twist length for neighboring pairs
  - Applications
    - \* Most common transmission media for both digital and analog signals

- \* Less expensive compared to coaxial cable or optical fiber
- \* Limited in terms of data rate and distance
- \* Telephone network
  - Individual units (residence lines) to local exchange (end office)
  - Subscriber loops
  - Supports voice traffic using analog signaling
  - May handle digital data at modest rates using modems
- \* Communications within buildings
  - Connection to digital data switch or digital PBX within a building
  - Allows data rate of 64 kbps
- Transmission characteristics
  - \* Requires amplifiers every 5-6 km for analog signals
  - \* Requires repeaters every 2-3 km for digital signals
  - \* Attenuation is a strong function of frequency
    - Higher frequency implies higher attenuation
  - \* Susceptible to interference and noise
  - \* Improvement possibilities
    - Shielding with metallic braids or sheathing reduces interference
    - Twisting reduces low frequency interference
    - Different twist length in adjacent pairs reduces crosstalk
- Unshielded and shielded twisted pairs
  - \* Unshielded twisted pair (UTP)
    - Ordinary telephone wire
    - Subject to external electromagnetic interference
  - \* Shielded twisted pair (STP)
    - Shielded with a metallic braid or sheath
    - Reduces interference
    - Better performance at higher data rates
    - More expensive and difficult to work compared to UTP
- Category 3 and Category 5 UTP
  - \* Most common is the 100-ohm voice grade twisted pair
  - \* Most useful for LAN applications
  - \* Category 3 UTP
    - Transmission characteristics specified up to 16 MHz
    - Voice grade cable in most office buildings
    - May have data rates up to 16 Mbps over limited distances
    - Typical twist length 7.5 to 10 cm
  - \* Category 4 UTP
    - Transmission characteristics specified up to 20 MHz
  - \* Category 5 UTP
    - Transmission characteristics specified up to 100 MHz
    - Data grade cable in newer buildings
    - May have data rates up to 100 Mbps over limited distances
    - Much more tightly twisted, with typical twist length 0.6 to 0.85 cm, for better performance
- Coaxial cable

- Physical description
  - \* Consists of two conductors with construction that allows it to operate over a wider range of frequencies compared to twisted pair
  - \* Hollow outer cylindrical conductor surrounding a single inner wire conductor
  - \* Inner conductor held in place by regularly spaced insulating rings or solid dielectrical material
  - \* Outer conductor covered with a jacket or shield
  - \* Diameter from 1 to 2.5 cm
  - \* Shielded concentric construction reduces interference and crosstalk
  - \* Can be used over longer distances and support more stations on a shared line than twisted pair
- Applications
  - \* Most common use is in cable TV
  - \* Traditionally part of long distance telephone network
  - \* Can carry more than 10,000 voice channels simultaneously using frequency-division multiplexing
  - \* Short range connections between devices
- Transmission characteristics
  - \* Used to transmit both analog and digital signals
  - \* Superior frequency characteristics compared to twisted pair
  - \* Can support higher frequencies and data rates
  - \* Shielded concentric construction makes it less susceptible to interference and crosstalk than twisted pair
  - \* Constraints on performance are attenuation, thermal noise, and intermodulation noise
  - \* Requires amplifiers every few kilometers for long distance transmission
  - \* Usable spectrum for analog signaling up to 500 MHz
  - \* Requires repeaters every few kilometers for digital transmission
  - \* For both analog and digital transmission, closer spacing is necessary for higher frequencies/data rates
- Optical fiber
  - Thin, flexible material to guide optical rays
  - Cylindrical cross-section with three concentric links
    1. Core
      - \* Innermost section of the fiber
      - \* One or more very thin (dia. 8-100  $\mu\text{m}$ ) strands or fibers
    2. Cladding
      - \* Surrounds each strand
      - \* Plastic or glass coating with optical properties different from core
      - \* Interface between core and cladding prevents light from escaping the core
    3. Jacket
      - \* Outermost layer, surrounding one or more claddings
      - \* Made of plastic and other materials
      - \* Protects from environmental elements like moisture, abrasions, and crushing
  - Comparison with twisted pair and coaxial cable
    - \* Capacity
      - Much higher bandwidth
      - Can carry hundreds of Gbps over tens of kms
    - \* Smaller size and light weight
      - Very thin for similar data capacity

- Much lighter and easy to support in terms of weight (structural properties)
- \* Significantly lower attenuation
- \* EM isolation
  - Not affected by external EM fields
  - Not vulnerable to interference, impulse noise, or crosstalk
  - No energy radiation; little interference with other devices; security from eavesdropping
- \* Greater repeater spacing
  - Lower cost and fewer error sources
- Applications
  - \* Long haul trunks
    - Increasingly common in telephone networks
    - About 1500km in length with high capacity (20000 to 60000 voice channels)
  - \* Metropolitan trunks
    - Average length of about 12 km with a capacity of 100,000 voice channels
    - Mostly repeaterless to join phone exchanges in metro areas
  - \* Rural exchange trunks
    - Circuit lengths from 40 to 160 km
    - Fewer than 5000 voice channels
    - Connect exchanges of different phone companies
  - \* Subscriber loops
    - Central exchange to subscriber
    - May be able to handle image and video in addition to voice and data
  - \* Local area networks
    - 100Mbps to 1Gbps capacity
    - Can support hundreds of stations on a campus
- Transmission characteristics
  - \* Single-encoded beam of light transmitted by total internal reflection
  - \* Transparent medium should have higher refractive index compared to surrounding medium
    - Refractive Index* – The ratio of the speed of light in a vacuum to the speed of light in a medium under consideration
  - \* Optical fiber acts as a waveguide for frequencies in the range of about  $10^{14}$  to  $10^{15}$  Hz (IR and visible regions of spectrum)
  - \* Step-index multimode
    - Rays at shallow angles are reflected and propagated along the fiber
    - Other rays are absorbed by the surrounding material
  - \* Multimode transmission
    - Allows for multiple propagation paths, with different path lengths and time to traverse the fiber
    - Signal elements can be spread over time
    - Limits the rate at which data can be accurately received
    - Best suited for transmission over very short distances
  - \* Single-mode transmission
    - Reduced fiber core will allow fewer angles to be reflected
    - Single transmission path reduces distortion
    - Typically used for long-distance applications
  - \* Graded-index multimode
    - Lies in between single-mode and multimode

- Higher refractive index at the center implies that the rays close to axis advance slowly compared to rays close to the cladding
- Light in the core curves helically reducing its traveling distance (does not zig zag off the cladding)
- Shorter path and higher speed makes light at periphery as well as at the axis travel at the same speed
- \* Light sources
  1. Light-emitting diode (LED)
    - Cheaper and works over a greater temperature range
    - Longer operational life
  2. Injection laser diode (ILD)
    - More efficient and can sustain greater data rates
- Wavelength-division multiplexing
  - \* Multiple beams of light at different frequencies can be transmitted simultaneously
  - \* Form of frequency-division multiplexing (FDM) commonly known as wavelength-division multiplexing (WDM)

## Wireless Transmission

- Transmission and reception are achieved using an antenna
  - Transmitter sends out the EM signal into the medium
  - Receiver picks up the signal from the surrounding medium
- Directional transmission
  - Transmitter sends out a focused EM beam
  - Transmitter and receiver antennae must be carefully aligned
  - More suitable for higher frequency signals
- Omnidirectional transmission
  - Transmitted signal spreads out in all directions
  - May be received by many antennae
- Frequency ranges for wireless transmission
  1. 2 GHz – 40 GHz
    - Microwave frequencies
    - Highly directional beams for point-to-point communications
    - Also used for satellite communication
  2. 30 MHz – 1 GHz
    - Broadcast radio range
    - Suitable for omnidirectional purposes
  3.  $3 \times 10^{11}$  Hz –  $2 \times 10^{14}$  Hz
    - Infrared portion of the spectrum
    - Useful for local point-to-point and multipoint applications within confined areas
    - TV remote
- Terrestrial microwave
  - Physical description

- \* Parabolic dish antenna, about 3m in diameter
- \* Fixed rigidly with a focused beam along line of sight to receiving antenna
- \* With no obstacles, maximum distance ( $d$ , in km) between antennae can be

$$d = 7.14\sqrt{Kh}$$

where  $h$  is antenna height and  $K$  is an adjustment factor to account for the bend in microwave due to earth's curvature, enabling it to travel further than the line of sight; typically  $K = \frac{4}{3}$

- \* Two microwave antennae at a height of 100m may be as far as

$$7.14 \times \sqrt{133} = 82km$$

- \* Long distance microwave transmission is achieved by a series of microwave relay towers

#### – Applications

- \* Long haul telecom service
- \* Fewer repeaters than coaxial cable but needs line of sight

#### – Transmission characteristics

- \* Frequencies in the range of 2 – 40 GHz
- \* Higher frequency implies higher bandwidth leading to higher data rates
- \* Loss  $L$  due to attenuation over distance  $d$  at wavelength  $\lambda$  is expressed as

$$L = 10 \log \left( \frac{4\pi d}{\lambda} \right)^2 \text{ dB}$$

- Loss varies as the square of distance
- For twisted pair and coaxial cable, loss varies logarithmically with distance
- \* Repeaters may be placed further apart compared to coaxial cable
- \* Attenuation may increase with rainfall, especially above 10 GHz
- \* Interference is a problem, leading to regulated assignment of frequencies

### • Satellite microwave

#### – Physical description

- \* Communication satellite is a microwave relay station between two or more ground stations (also called earth stations)
- \* Satellite uses different frequency bands for incoming (uplink) and outgoing (downlink) data
- \* A single satellite can operate on a number of frequency bands, known as *transponder channels* or *transponders*
- \* Geosynchronous orbit (35,784 km)
- \* Satellites cannot be too close to each other to avoid interference
  - Current standard requires a 4° displacement in the 4/6 GHz band and 3° displacement at 12/14 GHz
  - This limits the number of available satellites

#### – Applications

- \* Television/telephone/private business networks
- \* VSAT – Very small aperture terminals
  - Used to share a satellite capacity for data transmission

#### – Transmission characteristics

- \* Optimum frequency range in 1–10 GHz
- \* Below 1 GHz, significant noise from galactic, solar, and atmospheric noise, and terrestrial electronic devices

- \* Above 1 GHz, signal attenuated by atmospheric absorption and precipitation
- \* Most satellites use 5.925–6.425 GHz band for uplink and 4.2–4.7 GHz band for downlink (4/6 band)
- \* Propagation delay of about a quarter second due to long distance
  - Problems in error control and flow control
  - Inherently broadcast, leading to security problems
- Broadcast radio
  - Physical description
    - \* Omnidirectional transmission
    - \* No need for dish antennae
  - Applications
    - \* Frequencies from 3 kHz to 300 GHz
    - \* Radio/Television/Data networking
  - Transmission characteristics
    - \* 30 MHz to 1 GHz (UHF band) used for broadcast communications
    - \* Ionosphere transparent to radio waves above 30 MHz
      - Transmission limited to line of sight
      - Distant transmitters do not interfere with each other due to reflection from atmosphere
    - \* Less sensitive to attenuation from rainfall
    - \* Maximum distance between transmitter and receiver is given by same equation as microwave; same for attenuation
    - \* Impairment due to multipath interference
      - Reflection from land, water, natural, man-made objects
- Infrared
  - Limited to short distances and highly directional
  - Cannot penetrate walls
  - No licensing; no frequency allocation issues