

Short Quiz - 4
EE-390
Set B

Name: _____

ID No: _____

Execute the following program and find the contents of the required registers and the memory contents of the stack segment. Assume AX=BX=CX=DX=SI=DI=0 and all stack-memory contents are also initially zero.

```
Title "Quiz "  
.MODEL small  
.STACK 32  
.DATA  
.CODE  
    MOV     AX,@DATA  
    MOV     DS ,AX  
    MOV     ES, AX  
    MOV     SP, 00ADH  
    MOV     AX, 5229H  
    CMP     AX, 7865H  
    JA      121AH  
    PUSH   AX  
    PUSH   SP  
    CALL   SUB1  
CS:121AH :POP     DX  
CS:121CH :MOV     AX, 4C00H  
            INT     21H  
            SUB1  PROC NEAR  
                    MOV DX, SP  
                    MOV CX, 000AH  
                    MOV SI, 0050H  
                    MOV DI, 0500H  
                    CLD  
                    MOVSB  
                    RET  
            ENDP  
END
```

After executing the program,
find:

DX = _____ ;

SI = _____ ;

Write the appropriate values:

Stack Segment

| | |
|---------|--|
| SS:00AF | |
| SS:00AD | |
| SS:00AB | |
| SS:00A9 | |
| SS:00A7 | |
| SS:00A5 | |