

Name: KEY

Id#

ICS 233, Term 072

Computer Architecture & Assembly Language

Quiz# 3

Date: Saturday, March 15, 2008

Q.1. Fill the blanks in the following questions:

1. The MIPS processor is a **Reduced Instruction Set (RISC)** computer.
2. The MIPS processor has **32** general purpose registers.
3. The MIPS instructions are **32** bit wide, and there are **3** instructions formats called: **Register (R-Format), Immediate (I-Format), Jump (J-Format)**.
4. The difference between **add** and **addu** instructions is that **overflow causes an arithmetic exception for add instruction but not for addu instruction**.
5. The difference between **sll** and **sllv** instructions is **the shift amount is constant for sll instruction but variable and stored in a register for sllv**.

Q.2. Write the **minimum** required MIPS instructions to implement each of the following pseudo instructions:

1. **li \$s1, 0x12345678**
lui \$s1, 0x1234
ori \$s1, \$s1, 0x5678
2. **move \$s1, \$s2**
or \$s1, \$zero, \$s2
3. **bgt \$s1, \$s2, Next**
slt \$at, \$s2, \$s1
bne \$at, \$zero, Next
4. **bge \$s1, \$s2, Next**
slt \$at, \$s1, \$s2
beq \$at, \$zero, Next

5. **rol \$s1, \$s1, 4**

Note that this instruction should rotate the content of register \$s1 by 4 bits to the left. For example, if \$s1=0x12345678, after executing the instruction the content of \$s1 becomes \$s1=0x23456781.

```
srl $at, $s1, 28
```

```
sll $s1, $s1, 4
```

```
or $s1, $s1, $at
```

Q.3. Write the minimum required MIPS instructions to implement each of the following. Pseudo instruction can be used.

1. **Multiply** the content of register **\$s1** by **30** without using multiplication instructions.

```
sll $t1, $s1, 5           # $t1=32*$s1
```

```
sll $s1, $s1, 1          # $s1=2*$s1
```

```
subu $s1, $t1, $s1       # $s1=2*$s1
```

2. **if ((\$s1 > 0) && ((\$s2 < 100) || (\$s2 > \$s3))) {\$s4++;}**

```
ble $s1, $zero, EndIf
```

```
li $t1, 100
```

```
blt $s2, $t1, Skip
```

```
ble $s2, $s3, Endif
```

```
Skip:    addiu $s4, $s4, 1
```

```
EndIf:
```