

Electrical Engineering Department  
 EE-416 Analog Filter Design  
 Instructor: Dr. Hussain Alzaher  
 H.W.# 2  
 Due Saturday, Oct .26, 2005

1) Determine (estimate) the degrees necessary for a maximally flat, Chebyshev, inverse Chebyshev, and Cauer (elliptic) filter to meet the following requirements.

	$\alpha_{\max} [dB]$	$\alpha_{\min} [dB]$	$\omega_p [rad / s]$	$\omega_s [rad / s]$
(a)	0.1	62	900	1500
(b)	0.05	45	12 k	15 k
(c)	1.2	42	4200	5880
(d)	0.5	28	1 M	1.65 M
(e)	0.5	25	15 k	16.5 k

What is your conclusion?

2) Determine the attenuation at the frequencies  $2 \times \omega_s$  and  $10 \times \omega_s$  for case (b) of problem 1. What do you conclude?

3) Determine the transfer function of inverse Chebyshev, and Cauer (elliptic) lowpass filters that meets the following specifications

$$\alpha_{\max} = 0.25 dB, \alpha_{\min} = 18 dB, \omega_p = 1000 rad / s \text{ and } \omega_s = 1650 rad / s$$

4) Use Mat lab program to draw the magnitude and phase response for case (a) of problem 1. What do you observe?

5) Design a lowpass filter with an Inverse Chebyshev response satisfying the following specifications:  $\alpha_{\max} = 0.25$  dB,  $\alpha_{\min} = 18$  dB,  $\omega_p = 1000$  rad/s,  $\omega_s = 1400$  rad/s. Adjust the gain so the minimum value of  $\alpha(\omega)$  is 0 dB. Magnitude scale so that the element values in your circuit realization are in practical range

