

# KING FAHD UNIVERSITY OF PETROLEUM & MINERALS

## ELECTRICAL ENGINEERING DEPARTMENT

Dr. Ibrahim O. Habiballah

EE-306

### Key Solution

Quiz 3b      Sec.:      I.D.:      Ser#:      Name:

A single-phase 2300/230-V transformer has the following data obtained from open-circuit test (measurements from the low-voltage side) and short-circuit test (measurements from high-voltage side):

$$V_{oc} = 230 \text{ V (rated-voltage)}$$

$$I_{oc} = 2.0 \text{ A}$$

$$P_{oc} = 50 \text{ W}$$

$$V_{sc} = 47 \text{ V}$$

$$I_{sc} = 6.0 \text{ A (rated-current)}$$

$$P_{sc} = 160 \text{ W}$$

Q.1 The kVA rating is (3-points)

- a. 0.46
- b. 1.38
- c. 4.6
- d. 13.8

Q.2 The core loss is (2-points)

- a. 50 W.
- b. 110 W.
- c. 160 W.
- d. 210 W.

Q.3 The percentage efficiency of the transformer when delivering rated power (full-load output power) at unity power factor is (5-points)

- a. 98.50
- b. 98.85
- c. 99.64
- d. 100.00